




### 2-kanals DALI dim controller 2-channel DALI dim controller



- 2 kanaals DALI stuurbare dimmer
- Geschikt voor dimmen (PWM) van LEDstrips
- Compatibel met DALI protocol conform IEC62386
- Helderheid regelbaar tussen 0% en 100%
- Beschermd tegen kortsluiting en overbelasting

- 2 channel DALI controllable dimmer
- Suitable for (PWM) dimming LED strips
- Compatible with DALI protocol in accordance with IEC62386
- Brightness adjustable between 0% and 100%
- Protected against short circuit and overload

Voedingsspanning (Input voltage): 12Vdc/24Vdc  
 Maximale stroom bij 12Vdc/24Vdc (Maximum current by 12Vdc/24Vdc): 10A per kanaal (per channel)  
 Maximaal vermogen (maximum output) 24V: 480W max.  
 Maximaal vermogen (maximum output) 12V: 240W max.  
 Bedrijfstemperatuur (Operating temperature): -20°C - 60°C

46191063

1. DALI dimmer ingang  
DALI dimmer input
2. Uitgang  
Output
3. Voeding 12Vdc/24Vdc  
Power supply 12Vdc/24Vdc



Aansluitschema  
Base drawing

