



## PLAT-OH! TRIMLESS SOFT 93036 W

29514 9020 W

BESCHIKBAAR IN  
**ZWART** 29514 9020 B  
**GOUD KLEUR** 29514 9020 GC  
**WIT** 29514 9020 W



 [Bekijk op website](#)

### Algemene info

<b>LOCATIE</b>	binnen
<b>INSTALLATIE</b>	Plafond Inbouw
<b>ZAAGMAAT/OPENING (MM)</b>	rond - ØKIT
<b>INBOUWDIEPTE (MM)</b>	55
<b>STOF EN WATERDICHTHEID</b>	IP20
<b>GEWICHT (KG)</b>	0.2
<b>RICHTBAARHEID</b>	0° tot 30° zwenkbaar
<b>INFO</b>	REFLECTOR FL-36° EXCL.LED POWER SUPPLY 350mA-DC

### Elektrische info

<b>KLASSE</b>	III
<b>ENERGIE KLASSE</b>	F

### Info lichtbron

Lightsource Name	LED
Lichtbron	LED array 6W / CRI>90 (R9: 50) / 3000K-1800K / 623lm
TM-30-15 Waarden	Rf: 90 / Rg: 99
SDCM	SDCM2
Risk-groep	RG1
LM80	L90B10 > 50000
LED techniek (lichtbron)	623lm // 6W // 105lm/W
LED techniek (toestel)	425lm // 7W // 62lm/W

### Benodigdheden

MOUNTING KIT PLAT-OH! TRIMLESS  
 LED POWER SUPPLY 350mA-DC

Voor gedetailleerde montage gegevens, consulteer de handleiding: [29514\\_XXX0\\_HAND.pdf](#)

## PLAT-OH! TRIMLESS SOFT 93036 W

29514 9020 W










### PLAFOND COMPATIBILITEIT

Ceiling Type	Mounting Kit	
 <b>System ceiling</b>	 MOUNTING KIT PLAT-OH! TRIMLESS	Required
 <b>Plasterboard</b>	 MOUNTING KIT PLAT-OH! TRIMLESS	Required
 <b>Stucanet</b>	 MOUNTING KIT PLAT-OH! TRIMLESS	Required

**PLAT-OH! TRIMLESS SOFT 93036 W**


29514 9020 W

**VERVOLLEDIG UW SPECIFICATIE**

LED voedingen	#
 <p><b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1</p>	1->2 <input type="checkbox"/>
 <p><b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5</p>	1->2 <input type="checkbox"/>
 <p><b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL</p>	1->2 <input type="checkbox"/>
 <p><b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL</p>	1->2 <input type="checkbox"/>
 <p><b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6</p>	1->2 <input type="checkbox"/>
 <p><b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9</p>	1->4(4) <input type="checkbox"/>
 <p><b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7</p>	1->3(2) <input type="checkbox"/>
 <p><b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9</p>	1->2 <input type="checkbox"/>
 <p><b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5</p>	1->2(2) <input type="checkbox"/>

## PLAT-OH! TRIMLESS SOFT 93036 W

29514 9020 W



**300 90 69**

LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6)



**300 90 124**

LED POWER SUPPLY MULTI-POWER DIM7


1->2(2)



**300 90 125**

LED POWER SUPPLY MULTI-POWER MINI DIM5


1->2(2)



**21012 0021**

LED POWER SUPPLY MULTI POWER DIM1


1->3



**21012 0035**

LED POWER SUPPLY MULTI POWER DIM5


1->3



**21012 004W**

LED POWER SUPPLY MULTI-POWER WDL


1->4(4)



**21012 005W**

LED POWER SUPPLY MULTI-POWER COMPACT WDL


1->3



**21012 0268**

LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8


2->2



**21012 0298**

LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->2




**21012 0308**

LED POWER SUPPLY 350mA / 7,35W DIM8

1

# PLAT-OH! TRIMLESS SOFT 93036 W

29514 9020 W




**21032 0295**

LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->2



## Montage kit



**29510 0020** MOUNTING KIT PLAT-OH! TRIMLESS



Notes: