





## ENTERO RD-S TRIMLESS IP 93020 W

28450 9320 W

BESCHIKBAAR IN  
**ZWART** 28450 9320 B  
**GOUD KLEUR** 28450 9320 GC  
**WIT** 28450 9320 W



 [Bekijk op website](#)

### Algemene info

<b>LOCATIE</b>	binnen
<b>INSTALLATIE</b>	Plafond Inbouw
<b>ZAAGMAAT/OPENING (MM)</b>	rond - Ø KIT
<b>INBOUWDIEPTE (MM)</b>	115
<b>STOF EN WATERDICHTHEID</b>	IP44/20
<b>GEWICHT (KG)</b>	0.245
<b>RICHTBAARHEID</b>	0° tot 20° zwenkbaar, 355° roteerbaar
<b>INFO</b>	REFLECTOR FL-20° EXCL.LED POWER SUPPLY 350-500mA-DC

### Elektrische info

<b>KLASSE</b>	III
<b>ENERGIE KLASSE</b>	D

### Info lichtbron

Lightsource Name	LED
Lichtbron	LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 787-1089lm
TM-30-15 Waarden	Rf: 90 / Rg: 99
SDCM	SDCM1
Risk-groep	RG1
LM80	L90B10 > 50000
LED techniek (lichtbron)	1089lm // 8,6W // 127lm/W
LED techniek (toestel)	693lm // 10W // 70lm/W

### Benodigdheden

























MOUNTING KIT ENTERO ROUND S  
MOUNTING KIT AIR 105  
LED POWER SUPPLY 350 / 500mA-DC DIM

# ENTERO RD-S TRIMLESS IP 93020 W

28450 9320 W

Voor gedetailleerde montage gegevens, consulteer de handleiding: [28450\\_XXX0\\_HAND.pdf](#)

## PLAFOND COMPATIBILITEIT

Ceiling Type	Mounting Kit	
 <b>System ceiling</b>	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 <b>Plasterboard</b>	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 <b>Stucanet</b>	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 <b>Wood</b>	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 <b>Concrete + plaster</b>	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 <b>Lintel + plaster</b>	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 <b>Hollow-core slab + plaster</b>	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 <b>Stretched ceiling</b>	 MOUNTING KIT ENTERO RD-S CSC	Required
	 MOUNTING KIT ENTERO RD-S WSC	Required
 <b>Ventilation in plasterboard</b>	 MOUNTING KIT SIDE AIR ONLY 1	Required
	 MOUNTING KIT SIDE AIR 105	Required
	 MOUNTING KIT NO AIR 105	Required
 <b>Ventilation in concrete + plaster</b>	 MOUNTING KIT NO AIR 105	Required
	 MOUNTING KIT TOP AIR ONLY 1	Required

## ENTERO RD-S TRIMLESS IP 93020 W

28450 9320 W

### VERVOLLEDIG UW SPECIFICATIE


#### LED voedingen

#



**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1->2



**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->2



**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1->2



**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1->2



**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

1->2



**300 48 500 ED5** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->2



**300 48 500 MDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

1->2



**300 48 500 WDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

1->2




**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6

1->2 / 1->2

## ENTERO RD-S TRIMLESS IP 93020 W


28450 9320 W



**300 90 63**

LED POWER SUPPLY MULTI-POWER DIM9


1->4(4) / 1->3(3)



**300 90 64**

LED POWER SUPPLY MULTI-POWER DIM7


1->2(2) / 1->2(1)



**300 90 67**

LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9


1->2 / -



**300 90 68**

LED POWER SUPPLY MULTI-POWER DIM5

1->2(2) / 1->2(1)



**300 90 69**

LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6) / 1->6(4)



**300 90 124**

LED POWER SUPPLY MULTI-POWER DIM7

1->2(2) / 1->2(1)



**300 90 125**

LED POWER SUPPLY MULTI-POWER MINI DIM5

1->2(2) / 1->2(1)



**300 90 135**

LED POWER SUPPLY MULTI-POWER HV


3->4 / 2->4



**21012 0010**

LED POWER SUPPLY MULTI POWER

1->2 / 1->2



**21012 0021**











LED POWER SUPPLY MULTI POWER DIM1

1->3 / 1->2




**ENTERO RD-S TRIMLESS IP 93020 W**

28450 9320 W

	<b>21012 0035</b>	LED POWER SUPPLY MULTI POWER DIM5	1->3 / 1->2	<input type="checkbox"/>
	<b>21012 004W</b>	LED POWER SUPPLY MULTI-POWER WDL	1->4(4) / 1->3(3)	<input type="checkbox"/>
	<b>21012 005W</b>	LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->3 / 1->2	<input type="checkbox"/>
	<b>21012 0268</b>	LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8	2->2 / 2->2	<input type="checkbox"/>
	<b>21012 0278</b>	LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	1	<input type="checkbox"/>
	<b>21012 0288</b>	LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	2->2	<input type="checkbox"/>
	<b>21012 0298</b>	LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	1->2 / 1->2 / 1->2	<input type="checkbox"/>
	<b>21012 0308</b>	LED POWER SUPPLY 350mA / 7,35W DIM8	1	<input type="checkbox"/>
	<b>21012 0318</b>	LED POWER SUPPLY 500mA / 10W DIM8	1	<input type="checkbox"/>
	<b>21032 0295</b>	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	1->2	<input type="checkbox"/>

## ENTERO RD-S TRIMLESS IP 93020 W

28450 9320 W



**21032 0305**

LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->2




### Montage kit



**28400 0010** MOUNTING KIT ENTERO RD-S O.F.A.



### Montage kit spanplafond




**28400 0070** MOUNTING KIT ENTERO RD-S CSC



**28400 0130** MOUNTING KIT ENTERO RD-S WSC




### Montage kit - side air + light



**29810 0110** MOUNTING KIT SIDE AIR 105



### Montage kit - side air only



**29810 0100** MOUNTING KIT SIDE AIR ONLY 1




# ENTERO RD-S TRIMLESS IP 93020 W

28450 9320 W

## Montage kit - top air only

---




**29810 0200** MOUNTING KIT TOP AIR ONLY 1



## Montage kit - no air

---



**29810 0120** MOUNTING KIT NO AIR 105



Notes: