





ENTERO RD-S TRIMLESS 93020 W

28425 9320 W

BESCHIKBAAR IN
ZWART 28425 9320 B
GOUD KLEUR 28425 9320 GC
WIT 28425 9320 W



0-30°/355°



 [Bekijk op website](#)

Algemene info

| | |
|-------------------------------|--|
| LOCATIE | binnen |
| INSTALLATIE | Plafond Inbouw |
| ZAAGMAAT/OPENING (MM) | rond - Ø KIT |
| INBOUWDIEPTE (MM) | 105 |
| STOF EN WATERDICHTHEID | IP20 |
| GEWICHT (KG) | 0.235 |
| RICHTBAARHEID | 0° tot 30° zwenkbaar, 355° roteerbaar |
| INFO | REFLECTOR FL-20° EXCL.LED POWER SUPPLY 350-700mA-DC Optional REFLECTOR 45° available |

Elektrische info

| | |
|-----------------------|-----|
| KLASSE | III |
| ENERGIE KLASSE | E |

Info lichtbron

| | |
|--------------------------|--|
| Lightsource Name | LED |
| Lichtbron | LED array 5,8-12,4W / CRI>90 (R9: 52) / 3000K / 787-1467lm |
| TM-30-15 Waarden | Rf: 90 / Rg: 99 |
| SDCM | SDCM1 |
| Risk-groep | RG1 |
| LM80 | L90B10 > 50000 |
| LED techniek (lichtbron) | 1467lm // 12,4W // 118lm/W |
| LED techniek (toestel) | 1127lm // 14W // 79lm/W |

Opmerkingen

Max.500mA when using accessories

Benodigdheden

MOUNTING KIT ENTERO ROUND S
MOUNTING KIT AIR 105
LED POWER SUPPLY 350 / 500 / 700mA-DC DIM

ENTERO RD-S TRIMLESS 93020 W

28425 9320 W

Accessoires

ENTERO S HONEYCOMB
 ENTERO S LINEAR SPREAD LENS
 ENTERO S SPREAD LENS
 ENTERO S SOFTENING LENS
 ENTERO S GLASS SBL

Voor gedetailleerde montage gegevens, consulteer de handleiding: [28425_XXX0_HAND.pdf](#)










PLAFOND COMPATIBILITEIT

| Ceiling Type | Mounting Kit | |
|---|---|----------|
|  System ceiling |  MOUNTING KIT ENTERO RD-S O.F.A. | Required |
|  Plasterboard |  MOUNTING KIT ENTERO RD-S O.F.A. | Required |
|  Stucanet |  MOUNTING KIT ENTERO RD-S O.F.A. | Required |
|  Wood |  MOUNTING KIT ENTERO RD-S O.F.A. | Required |
|  Concrete + plaster |  MOUNTING KIT ENTERO RD-S O.F.A. | Required |
|  Lintel + plaster |  MOUNTING KIT ENTERO RD-S O.F.A. | Required |
|  Hollow-core slab + plaster |  MOUNTING KIT ENTERO RD-S O.F.A. | Required |
|  Stretched ceiling |  MOUNTING KIT ENTERO RD-S CSC | Required |
| |  MOUNTING KIT ENTERO RD-S WSC | Required |
|  Ventilation in plasterboard |  MOUNTING KIT SIDE AIR ONLY 1 | Required |
| |  MOUNTING KIT SIDE AIR 105 | Required |
| |  MOUNTING KIT NO AIR 105 | Required |
|  Ventilation in concrete + plaster |  MOUNTING KIT NO AIR 105 | Required |
| |  MOUNTING KIT TOP AIR 105 | Required |
| |  MOUNTING KIT TOP AIR ONLY 1 | Required |

ENTERO RD-S TRIMLESS 93020 W


28425 9320 W

VERVOLLEDIG UW SPECIFICATIE

| LED voedingen | # |
|---|-------------------------------|
|  300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 | 1->2 <input type="checkbox"/> |
|  300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 1->2 <input type="checkbox"/> |
|  300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL | 1->2 <input type="checkbox"/> |
|  300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL | 1->2 <input type="checkbox"/> |
|  300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 | 1->2 <input type="checkbox"/> |
|  300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 1->2 <input type="checkbox"/> |
|  300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL | 1->2 <input type="checkbox"/> |
|  300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL | 1->2 <input type="checkbox"/> |
|  300 48 700 ED1 LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM1 | 1->2 <input type="checkbox"/> |


ENTERO RD-S TRIMLESS 93020 W

28425 9320 W




300 48 700 ED5 LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5

1->2




300 48 700 MDL LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W MDL

1->2




300 48 700 WDL LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W WDL

1->2




300 90 61 LED POWER SUPPLY MULTI-POWER DIM6

1->2 / 1->2 / 1->2




300 90 63 LED POWER SUPPLY MULTI-POWER DIM9

1->4(4) / 1->3(3) / 1->3(3)




300 90 64 LED POWER SUPPLY MULTI-POWER DIM7

1->2(2) / 1->2(1) / 1->2(1)




300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

1->2 / - / 1->2



300 90 68 LED POWER SUPPLY MULTI-POWER DIM5

1->2(2) / 1->2(1) / 1->2(1)



300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6) / 1->6(4) / 1->4(3)




300 90 124 LED POWER SUPPLY MULTI-POWER DIM7

1->2(2) / 1->2(1) / 1(1)



ENTERO RD-S TRIMLESS 93020 W


28425 9320 W



300 90 125

LED POWER SUPPLY MULTI-POWER MINI DIM5


1->2(2) / 1->2(1) / 1(1)



300 90 135

LED POWER SUPPLY MULTI-POWER HV


3->4 / 2->4 / 2->4



21012 0010

LED POWER SUPPLY MULTI POWER


1->2 / 1->2 / 1->2



21012 0021

LED POWER SUPPLY MULTI POWER DIM1


1->3 / 1->2 / 1->2



21012 0035

LED POWER SUPPLY MULTI POWER DIM5


1->3 / 1->2 / 1->2



21012 004W

LED POWER SUPPLY MULTI-POWER WDL


1->4(4) / 1->3(3) / 1->3(3)



21012 005W

LED POWER SUPPLY MULTI-POWER COMPACT WDL


1->3 / 1->2 / 1->2



21012 0268

LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8


2->2 / 2->2



21012 0278

LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

1/1



21012 0288


LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

2->2 / 2->2



ENTERO RD-S TRIMLESS 93020 W


28425 9320 W



21012 0298

LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8


1->2 / 1->2 / 1->2 / 1



21012 0308

LED POWER SUPPLY 350mA / 7,35W DIM8


1



21012 0318

LED POWER SUPPLY 500mA / 10W DIM8


1



21012 0328

LED POWER SUPPLY 700mA / 15W DIM8


1



21032 0295

LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5


1->2



21032 0305

LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->2



21032 0315


LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5

1->2

Montage kit



28400 0010 MOUNTING KIT ENTERO RD-S O.F.A.




28500 0220 MOUNTING KIT DEEP ENTERO RD-S TRIMLESS

ENTERO RD-S TRIMLESS 93020 W

28425 9320 W

Montage kit spanplafond




28400 0070 MOUNTING KIT ENTERO RD-S CSC



28400 0130 MOUNTING KIT ENTERO RD-S WSC




Montage kit - side air + light



29810 0110 MOUNTING KIT SIDE AIR 105




Montage kit - top air + light



29810 0130 MOUNTING KIT TOP AIR 105



Montage kit - side air only




29810 0100 MOUNTING KIT SIDE AIR ONLY 1



ENTERO RD-S TRIMLESS 93020 W

28425 9320 W

Montage kit - top air only



29810 0200 MOUNTING KIT TOP AIR ONLY 1



Montage kit - no air




29810 0120 MOUNTING KIT NO AIR 105



ENTERO RD-S TRIMLESS 93020 W

28425 9320 W

Light veranderende onderdelen




28500 0010 ENTERO S LINEAR SPREAD LENS




28500 0020 ENTERO S SPREAD LENS



28500 0030 ENTERO S SOFTENING LENS



28500 0040 ENTERO S GLASS SBL



28500 0050 B ENTERO S HONEYCOMB SINGLE USE B



28500 0060 B ENTERO S HONEYCOMB DOUBLE USE B

Notes: