



# PLAT-OH! TRIMLESS SOFT 93036 W

29514 9020 W

DISPONIBLE EN  
**NOIR** 29514 9020 B  
**COULEUR OR** 29514 9020 GC  
**BLANC** 29514 9020 W



 [Voir sur le site Web](#)

## Informations générales

<b>EMPLACEMENT</b>	interieur
<b>INSTALLATION</b>	Plafond Encastré
<b>FORME / TAILLE DE DÉCOUPE (MM)</b>	circulaire - ØKIT
<b>PROFONDEUR D'ENCASTREMENT (MM)</b>	55
<b>PROTECTION CONTRE LA PÉNÉTRATION</b>	IP20
<b>POIDS (KG)</b>	0.2
<b>ORIENTATION</b>	0° à 30° inclinable
<b>INFORMATIONS</b>	REFLECTOR FL-36° EXCL.LED POWER SUPPLY 350mA-DC

## Informations électriques

<b>CLASSE</b>	III
<b>CLASSE D'ÉNERGIE</b>	F

## Info Source lumineuse

Lightsource Name	LED
Source de lumière	LED array 6W / CRI>90 (R9: 50) / 3000K-1800K / 623lm
Valeurs TM-30	Rf: 90 / Rg: 99
SDCM	SDCM2
Groupe de risque	RG1
LM80	L90B10 > 50000
Techniques LED (source lumineuse)	623lm // 6W // 105lm/W
Techniques LED (luminaire)	425lm // 7W // 62lm/W

## Conditions

MOUNTING KIT PLAT-OH! TRIMLESS  
 LED POWER SUPPLY 350mA-DC

Pour des instructions d'installation détaillées, veuillez consulter le manuel: [29514\\_XXX0\\_HAND.pdf](#)

## PLAT-OH! TRIMLESS SOFT 93036 W

29514 9020 W

### COMPATIBILITÉ DU PLAFOND

Ceiling Type	Mounting Kit	
 <b>System ceiling</b>	 MOUNTING KIT PLAT-OH! TRIMLESS	Required
 <b>Plasterboard</b>	 MOUNTING KIT PLAT-OH! TRIMLESS	Required
 <b>Stucanet</b>	 MOUNTING KIT PLAT-OH! TRIMLESS	Required

# PLAT-OH! TRIMLESS SOFT 93036 W

29514 9020 W

## TERMINEZ VOTRE SPÉCIFICATION

### les alimentations led

#



**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1->2



**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->2




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1->2




**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1->2




**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6

1->2




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9

1->4(4)




**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7

1->3(2)



**300 90 67** LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

1->2




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5

1->2(2)

## PLAT-OH! TRIMLESS SOFT 93036 W

29514 9020 W



**300 90 69**

LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6)



**300 90 124**

LED POWER SUPPLY MULTI-POWER DIM7


1->2(2)



**300 90 125**

LED POWER SUPPLY MULTI-POWER MINI DIM5


1->2(2)



**21012 0021**

LED POWER SUPPLY MULTI POWER DIM1


1->3



**21012 0035**

LED POWER SUPPLY MULTI POWER DIM5


1->3



**21012 004W**

LED POWER SUPPLY MULTI-POWER WDL


1->4(4)



**21012 005W**

LED POWER SUPPLY MULTI-POWER COMPACT WDL


1->3



**21012 0268**

LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8


2->2



**21012 0298**

LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->2




**21012 0308**

LED POWER SUPPLY 350mA / 7,35W DIM8

1

# PLAT-OH! TRIMLESS SOFT 93036 W

29514 9020 W




**21032 0295**

LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->2



## kit de montage



**29510 0020**

MOUNTING KIT PLAT-OH! TRIMLESS



Notes: