



PLAT-OH! TRIMLESS SOFT 93023 W

29514 9010 W

DISPONIBLE EN
NOIR 29514 9010 B
COULEUR OR 29514 9010 GC
BLANC 29514 9010 W



 [Voir sur le site Web](#)

Informations générales

EMPLACEMENT	interieur
INSTALLATION	Plafond Encastré
FORME / TAILLE DE DÉCOUPE (MM)	circulaire - ØKIT
PROFONDEUR D'ENCASTREMENT (MM)	55
PROTECTION CONTRE LA PÉNÉTRATION	IP20
POIDS (KG)	0.2
ORIENTATION	0° à 30° inclinable
INFORMATIONS	REFLECTOR FL-23° EXCL.LED POWER SUPPLY 350mA-DC

Informations électriques

CLASSE	III
CLASSE D'ÉNERGIE	F

Info Source lumineuse

Lightsource Name	LED
Source de lumière	LED array 6W / CRI>90 (R9: 50) / 3000K-1800K / 623lm
Valeurs TM-30	Rf: 90 / Rg: 99
SDCM	SDCM2
Groupe de risque	RG1
LM80	L90B10 > 50000
Techniques LED (source lumineuse)	623lm // 6W // 105lm/W
Techniques LED (luminaire)	448lm // 7W // 65lm/W

Conditions

MOUNTING KIT PLAT-OH! TRIMLESS
 LED POWER SUPPLY 350mA-DC

Pour des instructions d'installation détaillées, veuillez consulter le manuel: [29514_XXX0_HAND.pdf](#)

PLAT-OH! TRIMLESS SOFT 93023 W

29514 9010 W

COMPATIBILITÉ DU PLAFOND

Ceiling Type	Mounting Kit	
 System ceiling	 MOUNTING KIT PLAT-OH! TRIMLESS	Required
 Plasterboard	 MOUNTING KIT PLAT-OH! TRIMLESS	Required
 Stucanet	 MOUNTING KIT PLAT-OH! TRIMLESS	Required


PLAT-OH! TRIMLESS SOFT 93023 W

29514 9010 W

TERMINEZ VOTRE SPÉCIFICATION


les alimentations led

#




300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1->2




300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->2




300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1->2




300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1->2




300 90 61 LED POWER SUPPLY MULTI-POWER DIM6

1->2




300 90 63 LED POWER SUPPLY MULTI-POWER DIM9

1->4(4)




300 90 64 LED POWER SUPPLY MULTI-POWER DIM7

1->3(2)



300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

1->2




300 90 68 LED POWER SUPPLY MULTI-POWER DIM5

1->2(2)

PLAT-OH! TRIMLESS SOFT 93023 W

29514 9010 W



300 90 69

LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6)



300 90 124

LED POWER SUPPLY MULTI-POWER DIM7


1->2(2)



300 90 125

LED POWER SUPPLY MULTI-POWER MINI DIM5


1->2(2)



21012 0021

LED POWER SUPPLY MULTI POWER DIM1


1->3



21012 0035

LED POWER SUPPLY MULTI POWER DIM5


1->3



21012 004W

LED POWER SUPPLY MULTI-POWER WDL


1->4(4)



21012 005W

LED POWER SUPPLY MULTI-POWER COMPACT WDL


1->3



21012 0268

LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8


2->2



21012 0298

LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->2




21012 0308

LED POWER SUPPLY 350mA / 7,35W DIM8

1

PLAT-OH! TRIMLESS SOFT 93023 W

29514 9010 W




21032 0295

LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->2



kit de montage



29510 0020 MOUNTING KIT PLAT-OH! TRIMLESS



Notes: