






ENTERO RD-S TRIMLESS IP 92720 B

28450 9220 B

DISPONIBLE EN
NOIR 28450 9220 B
COULEUR OR 28450 9220 GC
BLANC 28450 9220 W



 [Voir sur le site Web](#)

Informations générales	
EMPLACEMENT	interieur
INSTALLATION	Plafond Encastré
FORME / TAILLE DE DÉCOUPE (MM)	circulaire - Ø KIT
PROFONDEUR D'ENCASTREMENT (MM)	115
PROTECTION CONTRE LA PÉNÉTRATION	IP44/20
POIDS (KG)	0.245
ORIENTATION	0° à 20° inclinable, 355° rotatif
INFORMATIONS	REFLECTOR FL-20° EXCL.LED POWER SUPPLY 350-500mA-DC

Informations électriques	
CLASSE	III
CLASSE D'ÉNERGIE	E

Info Source lumineuse	
Lightsource Name	LED
Source de lumière	LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm
Valeurs TM-30	Rf: 89 / Rg: 100
SDCM	SDCM1
Groupe de risque	RG1
LM80	L90B10 > 50000
Techniques LED (source lumineuse)	1041lm // 8,6W // 121lm/W
Techniques LED (luminaire)	663lm // 10W // 67lm/W

























Conditions	
MOUNTING KIT ENTERO ROUND S	
MOUNTING KIT AIR 105	
LED POWER SUPPLY 350 / 500mA-DC DIM	

Pour des instructions d'installation détaillées, veuillez consulter le manuel: [28450_XXX0_HAND.pdf](#)

ENTERO RD-S TRIMLESS IP 92720 B

28450 9220 B

COMPATIBILITÉ DU PLAFOND

Ceiling Type	Mounting Kit	
 System ceiling	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 Plasterboard	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 Stucanet	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 Wood	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 Concrete + plaster	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 Lintel + plaster	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 Hollow-core slab + plaster	 MOUNTING KIT ENTERO RD-S O.F.A.	Required
 Stretched ceiling	 MOUNTING KIT ENTERO RD-S CSC	Required
	 MOUNTING KIT ENTERO RD-S WSC	Required
 Ventilation in plasterboard	 MOUNTING KIT SIDE AIR ONLY 1	Required
	 MOUNTING KIT SIDE AIR 105	Required
	 MOUNTING KIT NO AIR 105	Required
 Ventilation in concrete + plaster	 MOUNTING KIT NO AIR 105	Required
	 MOUNTING KIT TOP AIR ONLY 1	Required

ENTERO RD-S TRIMLESS IP 92720 B

28450 9220 B

TERMINEZ VOTRE SPÉCIFICATION


les alimentations led

#




300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1->2




300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->2




300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1->2




300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1->2




300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

1->2




300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->2




300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

1->2



300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

1->2




300 90 61 LED POWER SUPPLY MULTI-POWER DIM6

1->2 / 1->2

ENTERO RD-S TRIMLESS IP 92720 B


28450 9220 B



300 90 63

LED POWER SUPPLY MULTI-POWER DIM9


1->4(4) / 1->3(3)



300 90 64

LED POWER SUPPLY MULTI-POWER DIM7


1->2(2) / 1->2(1)



300 90 67

LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9


1->2 / -



300 90 68

LED POWER SUPPLY MULTI-POWER DIM5

1->2(2) / 1->2(1)



300 90 69

LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6) / 1->6(4)



300 90 124

LED POWER SUPPLY MULTI-POWER DIM7


1->2(2) / 1->2(1)



300 90 125

LED POWER SUPPLY MULTI-POWER MINI DIM5


1->2(2) / 1->2(1)



300 90 135

LED POWER SUPPLY MULTI-POWER HV


3->4 / 2->4



21012 0010

LED POWER SUPPLY MULTI POWER

1->2 / 1->2



21012 0021











LED POWER SUPPLY MULTI POWER DIM1

1->3 / 1->2




ENTERO RD-S TRIMLESS IP 92720 B

28450 9220 B

	21012 0035	LED POWER SUPPLY MULTI POWER DIM5	1->3 / 1->2	<input type="checkbox"/>
	21012 004W	LED POWER SUPPLY MULTI-POWER WDL	1->4(4) / 1->3(3)	<input type="checkbox"/>
	21012 005W	LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->3 / 1->2	<input type="checkbox"/>
	21012 0268	LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8	2->2 / 2->2	<input type="checkbox"/>
	21012 0278	LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	1	<input type="checkbox"/>
	21012 0288	LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	2->2	<input type="checkbox"/>
	21012 0298	LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	1->2 / 1->2 / 1->2	<input type="checkbox"/>
	21012 0308	LED POWER SUPPLY 350mA / 7,35W DIM8	1	<input type="checkbox"/>
	21012 0318	LED POWER SUPPLY 500mA / 10W DIM8	1	<input type="checkbox"/>
	21032 0295	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	1->2	<input type="checkbox"/>

ENTERO RD-S TRIMLESS IP 92720 B

28450 9220 B



21032 0305

LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->2




kit de montage



28400 0010 MOUNTING KIT ENTERO RD-S O.F.A.



kit de montage plafond tendu




28400 0070 MOUNTING KIT ENTERO RD-S CSC




28400 0130 MOUNTING KIT ENTERO RD-S WSC



kit de montage - side air + light



29810 0100 MOUNTING KIT SIDE AIR ONLY 1




29810 0110 MOUNTING KIT SIDE AIR 105



ENTERO RD-S TRIMLESS IP 92720 B

28450 9220 B

kit de montage - top air only



29810 0200 MOUNTING KIT TOP AIR ONLY 1



kit de montage - no air



29810 0120 MOUNTING KIT NO AIR 105



Notes: