



## NIME II AIR 92752 PRIM

26412 9230 PRIM

BESCHIKBAAR IN  
GRONDLAAG 26412 9230 PRIM



 [Bekijk op website](#)

### Algemene info

<b>LOCATIE</b>	binnen
<b>INSTALLATIE</b>	Plafond Inbouw
<b>ZAAGMAAT/OPENING (MM)</b>	rond - Ø KIT
<b>STOF EN WATERDICHTHEID</b>	IP20
<b>GEWICHT (KG)</b>	0.2
<b>RICHTBAARHEID</b>	niet richtbaar
<b>INFO</b>	LENS WFL-52° EXCL.LED POWER SUPPLY 350-500mA-DC

### Elektrische info

<b>KLASSE</b>	III
<b>ENERGIE KLASSE</b>	G

### Info lichtbron

Lightsource Name	LED
Lichtbron	LED array 3,9-5,7W / CRI>90 (R9: 56) / 2700K / 385-519lm
TM-30-15 Waarden	Rf: 91 / Rg: 99
SDCM	SDCM2
Risk-groep	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED techniek (lichtbron)	519lm // 5,7W // 90lm/W
LED techniek (toestel)	335lm // 7W // 51lm/W

### Benodigdheden









MOUNTING KIT AIR 105  
LED POWER SUPPLY 350 / 500mA-DC DIM

Voor gedetailleerde montage gegevens, consulteer de handleiding: [26412\\_XXX0\\_HAND.pdf](#)

## NIME II AIR 92752 PRIM

26412 9230 PRIM

### PLAFOND COMPATIBILITEIT

Ceiling Type	Mounting Kit	
 <b>Ventilation in plasterboard</b>	 MOUNTING KIT SIDE AIR ONLY 1	Required
	 MOUNTING KIT SIDE AIR 105	Required
	 MOUNTING KIT NO AIR 105	Required
 <b>Ventilation in concrete + plaster</b>	 MOUNTING KIT NO AIR 105	Required
	 MOUNTING KIT TOP AIR 105	Required
	 MOUNTING KIT TOP AIR ONLY 1	Required


## NIME II AIR 92752 PRIM

26412 9230 PRIM

### VERVOLLEDIG UW SPECIFICATIE


#### LED voedingen

#




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1->3




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->3




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1->3




**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1->3




**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

1->3




**300 48 500 ED5** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->3




**300 48 500 MDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

1->3



**300 48 500 WDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

1->3




**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6

1->3 / 1->3

## NIME II AIR 92752 PRIM


26412 9230 PRIM



**300 90 63**

LED POWER SUPPLY MULTI-POWER DIM9


1->6(6) / 1->5(5)



**300 90 64**

LED POWER SUPPLY MULTI-POWER DIM7


2->4(3) / 1->4(2)



**300 90 67**

LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9


1->3



**300 90 68**

LED POWER SUPPLY MULTI-POWER DIM5

1->4(3) / 1->4(2) / 1->3(2)



**300 90 69**

LED POWER SUPPLY MULTI-POWER HV DIM9

3->9(9) / 1->9(6)



**300 90 124**

LED POWER SUPPLY MULTI-POWER DIM7


2->4(3) / 1->3(2) / 1->3(2)



**300 90 125**

LED POWER SUPPLY MULTI-POWER MINI DIM5


2->4(3) / 1->3(2) / 1->3(2)



**300 90 135**

LED POWER SUPPLY MULTI-POWER HV


5->7 / 4->7 / 4->6



**21012 0010**

LED POWER SUPPLY MULTI POWER

2->3 / 2->3



**21012 0021**


LED POWER SUPPLY MULTI POWER DIM1

2->4 / 2->4



## NIME II AIR 92752 PRIM


26412 9230 PRIM



**21012 0035**

LED POWER SUPPLY MULTI POWER DIM5


2->4 / 2->4



**21012 004W**

LED POWER SUPPLY MULTI-POWER WDL


1->6(6) / 1->5(5)



**21012 005W**

LED POWER SUPPLY MULTI-POWER COMPACT WDL


2->4 / 1->4 / 2->4



**21012 0258**

LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8


2->2



**21012 0268**

LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8


3->3



**21012 0278**

LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8


2->2



**21012 0288**

LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8


4->4



**21012 0298**

LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8


1->3 / 1->3 / 1->3



**21032 0295**

LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->3



**21032 0305**

LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->3




## NIME II AIR 92752 PRIM

26412 9230 PRIM

### Montage kit - side air + light

---




**29810 0110** MOUNTING KIT SIDE AIR 105



### Montage kit - top air + light

---




**29810 0130** MOUNTING KIT TOP AIR 105



### Montage kit - side air only

---




**29810 0100** MOUNTING KIT SIDE AIR ONLY 1



### Montage kit - top air only

---



**29810 0200** MOUNTING KIT TOP AIR ONLY 1



### Montage kit - no air

---



**29810 0120** MOUNTING KIT NO AIR 105





**NIME II AIR 92752 PRIM**

26412 9230 PRIM

Notes: